

NAME

ath3kfw - firmware download utility for Atheros AR3011/AR3012 chip based Bluetooth USB devices

SYNOPSIS

ath3kfw -d *device_name* **-f** *firmware_path*
ath3kfw -h

DESCRIPTION

The **ath3kfw** utility downloads the specified firmware file to the specified ugen(4) device.

This utility will *only* work with Atheros AR3011 and AR3012 chip based Bluetooth USB devices. The identification is currently based on USB vendor ID/product ID pair. The vendor ID should be 0x0cf3 (USB_VENDOR_ATHEROS2) and the product ID should be one of the supported devices.

Firmware files are available in the linux-firmware RPM.

The **ath3kfw** utility will query the device to determine which firmware image and board configuration to load in at runtime.

The options are as follows:

-D Enable verbose debugging.

-d *device_name*
Specify ugen(4) device name.

I Enable informational debugging.

-f *firmware_path*
Specify the directory containing the firmware files to search and upload.

-h Display usage message and exit.

EXIT STATUS

The **ath3kfw** utility exits 0 on success, and >0 if an error occurs.

SEE ALSO

libusb(3), ugen(4), devd(8)

AUTHORS

The original utility was written by Maksim Yevmenkin <m_evmenkin@yahoo.com>. This was written based on Linux ath3k by Adrian Chadd <adrian@freebsd.org>.

BUGS

Most likely. Please report if found.