

**NAME**

**btsckstat** - show Bluetooth sockets information

**SYNOPSIS**

**btsckstat** [-nrh] [-M *core*] [-p *protocol*]

**DESCRIPTION**

The **btsckstat** utility symbolically displays the contents of various Bluetooth sockets related data structures. There are few output formats, depending on the options for the information presented. The **btsckstat** utility will print results to the standard output and error messages to the standard error.

The options are as follows:

**-h**      Display usage message and exit.

**-M** *core*

Extract values associated with the name list from the specified core instead of the default */dev/kmem*.

**-n**      Show Bluetooth addresses as numbers. Normally, **btsckstat** attempts to resolve Bluetooth addresses, and display them symbolically.

**-p** *protocol*

Display a list of active sockets (protocol control blocks) for each specified protocol. Supported protocols are: **hci\_raw**, **l2cap\_raw**, **l2cap**, **rfcomm** and **rfcomm\_s**.

**-r**      Display a list of active routing entries (if any) for specified protocol.

**EXIT STATUS**

The **btsckstat** utility exits 0 on success, and >0 if an error occurs.

**SEE ALSO**

*ng\_btsocket*(4)

**AUTHORS**

Maksim Yevmenkin <*m\_evmenkin@yahoo.com*>

**BUGS**

Most likely. Please report if found.