

NAME

btsckstat - show Bluetooth sockets information

SYNOPSIS

btsckstat [-nrh] [-M *core*] [-p *protocol*]

DESCRIPTION

The **btsckstat** utility symbolically displays the contents of various Bluetooth sockets related data structures. There are few output formats, depending on the options for the information presented. The **btsckstat** utility will print results to the standard output and error messages to the standard error.

The options are as follows:

-h Display usage message and exit.

-M *core*

Extract values associated with the name list from the specified core instead of the default */dev/kmem*.

-n Show Bluetooth addresses as numbers. Normally, **btsckstat** attempts to resolve Bluetooth addresses, and display them symbolically.

-p *protocol*

Display a list of active sockets (protocol control blocks) for each specified protocol. Supported protocols are: **hci_raw**, **l2cap_raw**, **l2cap**, **rfcomm** and **rfcomm_s**.

-r Display a list of active routing entries (if any) for specified protocol.

EXIT STATUS

The **btsckstat** utility exits 0 on success, and >0 if an error occurs.

SEE ALSO

[ng_btsocket\(4\)](#)

AUTHORS

Maksim Yevmenkin <m_evmenkin@yahoo.com>

BUGS

Most likely. Please report if found.