

NAME

bus_get_resource - read a resource range/value with a given resource ID

SYNOPSIS

```
#include <sys/param.h>
```

```
#include <sys/bus.h>
```

```
#include <sys/rman.h>
```

int

```
bus_get_resource(device_t dev, int type, int rid, rman_res_t *startp, rman_res_t *countp);
```

DESCRIPTION

The **bus_get_resource()** function reads the range or value of the resource *type*, *rid* pair and stores it in the *startp* and *countp* arguments.

The arguments are as follows:

dev The device to read the resource from.

type The type of resource you want to read. It is one of:

SYS_RES_IRQ	for IRQs
SYS_RES_DRQ	for ISA DMA lines
SYS_RES_MEMORY	for I/O memory
SYS_RES_IOPORT	for I/O ports

rid A bus-specific handle that identifies the resource being read.

startp A pointer to the start address of this resource.

countp

A pointer to the length of the resource. For example, the size of the memory in bytes.

RETURN VALUES

Zero is returned on success, otherwise an error is returned.

SEE ALSO

bus_set_resource(9), device(9), driver(9)

AUTHORS

This manual page was written by Sascha Wildner.