

NAME

device_enable, **device_disable**, **device_is_enabled** - manipulate device enabled flag

SYNOPSIS

```
#include <sys/param.h>
```

```
#include <sys/bus.h>
```

```
void
```

```
device_enable(device_t dev);
```

```
void
```

```
device_disable(device_t dev);
```

```
int
```

```
device_is_enabled(device_t dev);
```

DESCRIPTION

Each device has an enabled flag associated with it. A device is enabled by default when it is created but may be disabled (for instance to prevent a destructive or time consuming probe attempt). To disable a device, call **device_disable()**, to re-enable it, call **device_enable()** and to test to see if a device is enabled, call **device_is_enabled()**.

SEE ALSO

device(9)

AUTHORS

This manual page was written by Doug Rabson.