

NAME

poudriere status - Show status of current and previous builds.

SYNOPSIS

poudriere status [*options*]

DESCRIPTION

This command shows status of current and previous builds. The output is sorted by SETNAME, PORTSTREE, JAILNAME and then BUILDNAME.

OPTIONS

- a** Show all builds, not just latest. This implies **-f**.
- B name** Specifies which buildname to match on. This supports shell globbing. Defaults to "latest". Specifying this implies the **-f** flag.
- b** Show details about what each builder for the matched builds are doing.
- c** Show a more compact output and do not include some columns.
- f** Show finished builds, not just currently running. This is implied by the **-a**, **-B** and **-r** flags.
- H** Do not print headers and separate fields by a single tab instead of arbitrary white space.
- j name** Specifies the *name* of the jail to filter by.
- l** Show logs instead of URL.
- p tree** This flag specifies which ports *tree* to filter builds by.
- r** Show build results. This implies the **-f** flag.
- z set** This specifies which SET to filter builds by. Use **0** to match on empty SET.

SEE ALSO

poudriere(8), poudriere-bulk(8), poudriere-distclean(8), poudriere-image(8), poudriere-jail(8), poudriere-logclean(8), poudriere-options(8), poudriere-pkgclean(8), poudriere-ports(8), poudriere-queue(8), poudriere-testport(8), poudriere-version(8)

AUTHORS

Baptiste Daroussin <bapt@FreeBSD.org>
Bryan Drewery <bdrewery@FreeBSD.org>