

**NAME**

rdma\_get\_devices - Get a list of RDMA devices currently available.

**SYNOPSIS**

```
#include <rdma/rdma_cma.h>
```

```
struct ibv_context ** rdma_get_devices (int *num_devices);
```

**ARGUMENTS**

num\_devices If non-NULL, set to the number of devices returned.

**DESCRIPTION**

Return a NULL-terminated array of opened RDMA devices. Callers can use this routine to allocate resources on specific RDMA devices that will be shared across multiple rdma\_cm\_id's.

**RETURN VALUE**

Returns an array of available RDMA devices, or NULL if the request fails. On failure, errno will be set to indicate the failure reason.

**NOTES**

The returned array must be released by calling rdma\_free\_devices. Devices remain opened while the librdmacm is loaded.

**SEE ALSO**

rdma\_free\_devices(3)