

NAME

`rdma_set_option` - Set communication options for an `rdma_cm_id`.

SYNOPSIS

```
#include <rdma/rdma_cma.h>
```

```
int rdma_set_option (struct rdma_cm_id *id, int level, int optname, void *optval, size_t optlen);
```

ARGUMENTS

`id` RDMA identifier.

`level` Protocol level of the option to set.

`optname` Name of the option, relative to the level, to set.

`optval` Reference to the option data. The data is dependent on the level and `optname`.

`optlen` The size of the %`optval` buffer.

DESCRIPTION

Sets communication options for an `rdma_cm_id`. This call is used to override the default system settings.

RETURN VALUE

Returns 0 on success, or -1 on error. If an error occurs, `errno` will be set to indicate the failure reason.

NOTES

Option details may be found in the relevant header files.

SEE ALSO

`rdma_create_id(3)`