

**NAME**

**xdpr** - dump an X window directly to a printer

**SYNOPSIS**

**xdpr** [*filename*] [ **-display** *host:display* ] [ **-Pprinter** ] [ **-device** *devtype* ] [ *option* ... ]

**DESCRIPTION**

*Xdpr* uses the commands *xwd*, *xpr*, and *lpr* or *lp* to dump an X window, process it for a particular printer type, and print it out on the printer of your choice. This is the easiest way to get a printout of a window. *Xdpr* by default will print the largest possible representation of the window on the output page.

The options for *xdpr* are the same as those for *xpr*, *xwd*, and *lpr* or *lp*. The most commonly-used options are described below; see the manual pages for these commands for more detailed descriptions of the many options available.

**OPTIONS**

*filename*

Specifies a file containing a window dump (created by *xwd*) to be printed instead of selecting an X window.

**-Pprinter**

Specifies a printer to send the output to. If a printer name is not specified here, *xdpr* (really, *lpr* or *lp*) will send your output to the printer specified by the *PRINTER* environment variable. Be sure that type of the printer matches the type specified with the *-device* option.

**-display** *host:display* [*.screen*]

Normally, *xdpr* gets the host and display number to use from the environment variable “DISPLAY.” One can, however, specify them explicitly; see *X(1)*.

**-device** *devtype*

Specifies the device on which the file will be printed. Currently supported:

**la100**

Digital LA100

**ljet** HP LaserJet series and other monochrome PCL devices such as ThinkJet, QuietJet, RuggedWriter, HP2560 series, and HP 2930 series printers

**ln03**

Digital LN03

**pjet** HP PaintJet (color mode)

**pjetxl**

HP HP PaintJet XL Color Graphics Printer (color mode)

**pp** IBM PP3812**ps** PostScript printer

The default is PostScript. **-device lw** (LaserWriter) is equivalent to **-device ps** and is provided only for backwards compatibility.

**-help**

This option displays the list of options known to *xdpr*.

Any other arguments will be passed to the *xwd*, *xpr*, and *lpr* or *lp* commands as appropriate for each.

**SEE ALSO**

*xwd*(1), *xpr*(1), *lpr*(1), *lp*(1), *xwud*(1), *X*(7)

**ENVIRONMENT**

**DISPLAY** which display to use by default.

**PRINTER** which printer to use by default.

**COPYRIGHT**

Copyright X Consortium

See *X*(7) for a full statement of rights and permissions.

**AUTHORS**

Paul Boutin, MIT Project Athena

Michael R. Gretzinger, MIT Project Athena

Jim Gettys, MIT Project Athena