NAME

atan2, **atan2f**, **atan2l**, **carg**, **cargf**, **cargl** - arc tangent and complex phase angle functions

LIBRARY

Math Library (libm, -lm)

SYNOPSIS

#include <math.h>

double
atan2(*double y*, *double x*);

float
atan2f(*float y*, *float x*);

long double
atan2l(*long double y*, *long double x*);

#include <complex.h>

double
carg(*double complex z*);

float
cargf(*float complex z*);

long double
cargl(*long double complex z*);

DESCRIPTION

The **atan2**(), **atan2f**(), and **atan2l**() functions compute the principal value of the arc tangent of *y/x*, using the signs of both arguments to determine the quadrant of the return value.

The **carg**(), **cargf**(), and **cargl**() functions compute the complex argument (or phase angle) of *z*. The complex argument is the number theta such that z = r * e^(I * theta), where r = cabs(z). The call carg(z) is equivalent to atan2(cimag(z), creal(z)), and similarly for **cargf**() and **cargl**().

RETURN VALUES

The **atan2**(), **atan2f**(), and **atan2l**() functions, if successful, return the arc tangent of *y/x* in the range [-pi, +pi] radians. Here are some of the special cases:

$$\mathbf{atan2}(y, x) := \begin{array}{ll} \mathbf{atan}(y/x) & \text{if } x > 0, \\ \text{sign}(y)*(\text{pi} - \mathbf{atan}(|y/x|)) & \text{if } x < 0, \\ 0 & \text{if } x = y = 0, \text{ or} \\ \text{sign}(y)*\text{pi}/2 & \text{if } x = 0 \mathrel{!=} y. \end{array}$$

NOTES

The function **atan2**() defines "if x > 0," **atan2**(*0, 0*) = 0 despite that previously **atan2**(*0, 0*) may have generated an error message. The reasons for assigning a value to **atan2**(*0, 0*) are these:

1. Programs that test arguments to avoid computing **atan2**(*0, 0*) must be indifferent to its value. Programs that require it to be invalid are vulnerable to diverse reactions to that invalidity on diverse computer systems.

2. The **atan2**() function is used mostly to convert from rectangular (x,y) to polar (r,theta) coordinates that must satisfy x = r*cos theta and y = r*sin theta. These equations are satisfied when (x=0,y=0) is mapped to (r=0,theta=0). In general, conversions to polar coordinates should be computed thus:

    ```
    r      := hypot(x,y);  ... := sqrt(x*x+y*y)
    theta  := atan2(y,x).
    ```

3. The foregoing formulas need not be altered to cope in a reasonable way with signed zeros and infinities on a machine that conforms to IEEE 754; the versions of hypot(3) and **atan2**() provided for such a machine are designed to handle all cases. That is why **atan2**(*+-0, -0*) = +-pi for instance. In general the formulas above are equivalent to these:

    ```
    r := sqrt(x*x+y*y); if r = 0 then x := copysign(1,x);
    ```

SEE ALSO

acos(3), asin(3), atan(3), cabs(3), cos(3), cosh(3), math(3), sin(3), sinh(3), tan(3), tanh(3)

STANDARDS

The **atan2**(), **atan2f**(), **atan2l**(), **carg**(), **cargf**(), and **cargl**() functions conform to ISO/IEC 9899:1999 ("ISO C99").