

NAME

pam_echo - Echo PAM module

SYNOPSIS

[service-name] module-type control-flag pam_echo [arguments]

DESCRIPTION

The echo service module for PAM displays its arguments to the user, separated by spaces, using the current conversation function.

If the **%** character occurs anywhere in the arguments to **pam_echo**, it is assumed to introduce one of the following escape sequences:

%H The name of the host on which the client runs (PAM_RHOST).

%s The current service name (PAM_SERVICE).

%t The name of the controlling tty (PAM_TTY).

%U The applicant's user name (PAM_RUSER).

%u The target account's user name (PAM_USER).

Any other two-character sequence beginning with **%** expands to the character following the **%** character.

SEE ALSO

pam.conf(5), pam(3)

AUTHORS

The **pam_echo** module and this manual page were developed for the FreeBSD Project by ThinkSec AS and NAI Labs, the Security Research Division of Network Associates, Inc. under DARPA/SPAWAR contract N66001-01-C-8035 ("CBOSS"), as part of the DARPA CHATS research program.